

# FATEK<sup>®</sup> AUTOMATION CORPORATION

26FL., NO. 29, SEC. 2, JUNGJENG E. RD., DANSHUEI DIST.,  
NEW TAIPEI CITY 25170, TAIWAN, R.O.C.

TEL : +886-2-2808-2192  
FAX : +886-2-2809-2618  
E-mail : sales@fatek.com  
tech@fatek.com  
Website : www.fatek.com

The specifications are subject to change without prior notice.

B1-CV2-06-2018

**FATEK<sup>®</sup>** The Brand You Can Rely On

Since 1992



## Economical and High-Quality PLC

**FATEK** B1/B1z Series Micro-Programmable Controllers



[www.fatek.com](http://www.fatek.com)



# Be impressed with the high quality!

## Features

### Core Technology of the Advanced SoC

With advanced software, hardware techniques and over 20 years experience in the automation industry, FATEK has integrated its own SoC CPU (Systems on Chip), hardware logic solver (HLS), hardware high-speed counter/timer, NC positioning, communication, FLASH, and SRAM into a tiny BGA chip. This is an industry first making FATEK a market leader in micro PLC design!

### Compact and Rugged

Common components are now integrated into the SoC, so the processor and I/O board layer can now be manufactured on a single PCB substantially reducing the overall size and increasing the reliability of the B1/B1z series controllers!

### High Quality and High Reliability

With the streamline hardware design and the highly integrated SoC technology, the quantity of the components required in the B1/B1z

series PLC is significantly reduced. With the combination of the high quality parts rigorous quality control procedures, FATEK creates a high quality PLC for today's industry.

### Competitive Low Price

The streamline design of SoC technology significantly reduces the hardware costs. The B1/B1z series PLC incorporates the most sophisticated manufacturing process and high quality two-layer board design, and have better noise immunity than other four-layer PLC board design. This makes the B1/B1z PLC very price-competitive in today's cost-conscious PLC market!


### Easy to Use, Common Instruction Sets

The B1/B1z series PLC is an economic type PLC without any compromise to its performance. It also provides all the easy to use yet powerful FBs series PLC's instructions. Both B1/B1z and FBs series PLC are programmed by the same utility software - Winproladder.





# System Configuration



Environmental Specifications

| Item                          |                  | Specification                                 | Note                 |
|-------------------------------|------------------|-----------------------------------------------|----------------------|
| Storage temperature           |                  | -25°~70°C                                     |                      |
| Operating ambient temperature |                  | 0°~55°C                                       |                      |
| Relative humidity             |                  | 5~95%                                         | Non-condensing, RH-2 |
| Pollution resistance          |                  | Degree II                                     |                      |
| Corrosion resistance          |                  | Based on IEC-68 standard                      |                      |
| Altitude                      |                  | ≤2000m                                        |                      |
| Vibration resistance          | Fixd by DIN rail | 0.5G, 2 hours for each direction of 3 axes    |                      |
|                               | Fasten by screw  | 2G, 2 hours for each direction of 3 axes      |                      |
| Shock resistance              |                  | 10G, three times for each direction of 3 axes |                      |
| Noise resistance              |                  | 1500Vp-p, pulse width 1μS                     |                      |
| Withstand voltage             |                  | 500VAC, 1 minute (DC)                         | L, N to any terminal |
|                               |                  | 1500VAC, 1 minute (AC)                        |                      |

DC Model Power Specifications

| Specification                               | Item | 10/14 Points Main Unit | 20/24 Points Main Unit | 32/40 Points Main Unit | 60 Points Main Unit |
|---------------------------------------------|------|------------------------|------------------------|------------------------|---------------------|
| Input voltage                               |      | 24VDC,-15%/+20%        |                        |                        |                     |
| Max. power capability                       |      | 2.5W/3W                | 3.5W/4W                | 4.5W/5W                | 6W                  |
| Inrush current                              |      | 20A@24VDC              |                        |                        |                     |
| Allowable power momentary interruption time |      | <2ms                   |                        |                        |                     |
| Fuse rating                                 |      | 2A,125VDC              |                        |                        |                     |

AC Model Power Specifications (custom products)

| Specification                                           | Item | 10/14 Ponits Main Unit  | 20/24 Ponits Main Unit | 32/40 Ponits Main Unit | 60 Ponits Main Unit |
|---------------------------------------------------------|------|-------------------------|------------------------|------------------------|---------------------|
| Input power/Frequency                                   |      | 85 ~ 264VAC / 50 ~ 60Hz |                        |                        |                     |
| Max. power capability<br>(Built-in sensor power supply) |      | 21W                     |                        |                        |                     |
| Inrush current                                          |      | 20A@264VAC              |                        |                        |                     |
| Allowable power momentary interruption time             |      | <20mS                   |                        |                        |                     |
| Fuse rating                                             |      | 2A, 250VAC              |                        |                        |                     |

Main Unit Specifications

| Specification            |                                                          |                    | Item            | B1                                        | B1z                                    | Note                                                                                                                        |
|--------------------------|----------------------------------------------------------|--------------------|-----------------|-------------------------------------------|----------------------------------------|-----------------------------------------------------------------------------------------------------------------------------|
| Execution speed          |                                                          |                    |                 | 0.33uS / Sequential instruction           |                                        |                                                                                                                             |
| Memory capacity          |                                                          | Program (Word)     |                 | 7936 Words                                | 3840 Words                             |                                                                                                                             |
|                          |                                                          | Comment (Byte)     |                 | 8K Bytes                                  | 4K Bytes                               |                                                                                                                             |
| Program memory           |                                                          |                    |                 | FLASH ROM or SRAM+Lithium battery Back-up |                                        |                                                                                                                             |
| Sequential instruction   |                                                          |                    |                 | 36 instructions                           |                                        |                                                                                                                             |
| Function instruction     |                                                          |                    |                 | 326 instructions(126 kinds)               | 323 instructions(123 kinds)            | Include derivative instructions                                                                                             |
| Flow chart command (SFC) |                                                          |                    |                 | 4 instructions                            |                                        |                                                                                                                             |
| Communication Interface  | Port0 (RS232)<br>Speed 4.8k~115.2kbps                    |                    |                 | Built- in                                 |                                        | Default setting of each port is 906 kbps, Port1~2 provides FATEK or Modbus RTU/ASCII or user defined communication protocol |
|                          | Port1~2 (RS232, RS485, Ethernet)<br>Speed 4.8k~921.6kbps |                    |                 | Expandable Port1 and Port2                | Built-in Port2(RS485)<br>No expandable |                                                                                                                             |
|                          | Maximum link stations                                    |                    |                 | 254                                       |                                        |                                                                                                                             |
| Digital (Bit status)     | X                                                        | Input contact (DI) |                 | X+Y=128                                   | 6 / 8 / 12 / 14 / 20 / 24 / 36         | Corresponding to external digital input                                                                                     |
|                          | Y                                                        | Output relay (DO)  |                 |                                           | 4 / 6 / 8 / 10 / 12 / 16 / 24          | Corresponds to external digital output                                                                                      |
|                          | TR                                                       |                    | Temporary relay |                                           | TR0~TR39 (40)                          |                                                                                                                             |
|                          | M                                                        | Internal relay     | Non-retentive   | M0~M799 (800)* <sup>1</sup>               |                                        | Can be configured as retentive type                                                                                         |
|                          |                                                          |                    |                 | M1400~M1911 (512)                         |                                        |                                                                                                                             |
|                          |                                                          |                    |                 | Retentive                                 | M800~M1399 (600)* <sup>1</sup>         |                                                                                                                             |
|                          | Special relay                                            |                    |                 | M1912~M2001 (90)                          |                                        |                                                                                                                             |

\*1 : Default, changeable by user  
\*2 : LAIO and L4MTC module will occupy Port1

(Continue)


| Specification                    |                                           |                                   | Item                                                                      | B1                                                         |                       |              | B1z                                        |             |                                                                                                                                                                   | Note                                                                                            |                                                |
|----------------------------------|-------------------------------------------|-----------------------------------|---------------------------------------------------------------------------|------------------------------------------------------------|-----------------------|--------------|--------------------------------------------|-------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------|------------------------------------------------|
| Digital (Bit status)             | S                                         | Step relay                        | Non-retentive                                                             | S0~S499 (500)*1                                            |                       |              |                                            |             |                                                                                                                                                                   | S20~S499 can be configures as retentive type                                                    |                                                |
|                                  |                                           |                                   | Retentive                                                                 | S500~S999 (500)*1                                          |                       |              |                                            |             |                                                                                                                                                                   | Can be configures as non-retentive type                                                         |                                                |
|                                  | T                                         | Timer "Time-Up" status contact    |                                                                           |                                                            | T0~T255 (256)         |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
|                                  | C                                         | Counter "Count-Up" status contact |                                                                           |                                                            | C0~C255 (256)         |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
| Register (Word data)             | TMR                                       | Time current value register       | 0.01S Time base                                                           | T0~T49 (50)*1                                              |                       |              |                                            |             |                                                                                                                                                                   | T0~T255 members for each time base can be adjusted                                              |                                                |
|                                  |                                           |                                   | 0.1S Time base                                                            | T50~T199 (150)*1                                           |                       |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
|                                  |                                           |                                   | 1S Time base                                                              | T200~T255 (56)*1                                           |                       |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
|                                  | CTR                                       | Counter current value register    | 16-bit                                                                    | Retentive                                                  | C0~C139 (140)*1       |              |                                            |             |                                                                                                                                                                   |                                                                                                 | Can be configured as non-retentive type        |
|                                  |                                           |                                   |                                                                           | Non-retentive                                              | C140~C199 (60)*1      |              |                                            |             |                                                                                                                                                                   |                                                                                                 | Can be configured as retentive type            |
|                                  |                                           |                                   | 32-bit                                                                    | Retentive                                                  | C200~C239 (40)*1      |              |                                            |             |                                                                                                                                                                   |                                                                                                 | Can be configured as non-retentive type        |
|                                  |                                           |                                   |                                                                           | Non-retentive                                              | C240~C255 (16)*1      |              |                                            |             |                                                                                                                                                                   |                                                                                                 | Can be configured as retentive type            |
|                                  | HR DR                                     | Data register                     | Retentive                                                                 | R0~R2999 (3000)*1                                          |                       |              |                                            |             |                                                                                                                                                                   | Can be configured as non-retentive type                                                         |                                                |
|                                  |                                           |                                   |                                                                           | D0~D3999 (4000)                                            |                       |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
|                                  |                                           |                                   |                                                                           | R5000~R8071 (3072)*1                                       |                       |              |                                            |             |                                                                                                                                                                   | When not configured as ROR, it can serve normal register (for read/write)                       |                                                |
|                                  |                                           |                                   |                                                                           | R3000~R3839 (840)*1                                        |                       |              |                                            |             |                                                                                                                                                                   | Can be configured as retentive type                                                             |                                                |
|                                  | ROR                                       |                                   | Read only register                                                        | R5000~R8071 can be set as ROR, default setting is (0)*1    |                       |              |                                            |             |                                                                                                                                                                   | ROR is stored in special ROR area and not occupy program space                                  |                                                |
|                                  | FR                                        |                                   | File register                                                             | F0~F8191 (8192)                                            |                       |              |                                            |             |                                                                                                                                                                   | Saved/retrieved via dedicated instruction                                                       |                                                |
|                                  | IR                                        | Input register                    |                                                                           |                                                            | R3840~R3857 (18)      |              |                                            | -           |                                                                                                                                                                   |                                                                                                 | Corresponding to the external numerical input  |
|                                  | OR                                        | Output register                   |                                                                           |                                                            | R3904~R3921 (18)      |              |                                            | -           |                                                                                                                                                                   |                                                                                                 | Corresponding to the external numerical output |
|                                  | SR                                        | Special system register           |                                                                           | R3968~R4167 (200)                                          |                       |              |                                            |             |                                                                                                                                                                   | D4072~4075(4)corresponds LAIO Module inputs*2<br>D4076~4077(4)corresponds LAIO Module outputs*2 |                                                |
|                                  |                                           |                                   |                                                                           | D4000~D4095 (96)                                           |                       |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
|                                  |                                           | 0.1mS High-speed timer register   |                                                                           |                                                            | R4152~R4154 (3)       |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
|                                  |                                           | High-speed counter register       | Hardware(4 sets)                                                          | DR4096~DR4110 (4x4)                                        |                       |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
|                                  |                                           |                                   | Software(4sets)                                                           | DR4112~DR4126 (4x4)                                        |                       |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
|                                  |                                           | Calendar register                 |                                                                           |                                                            | R4128 (sec)           | R4129 (min)  | R4130 (hour)                               | R4131 (day) | -                                                                                                                                                                 |                                                                                                 |                                                |
|                                  | R4132 (month)                             |                                   |                                                                           |                                                            | R4133 (year)          | R4134 (week) |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
|                                  | XR                                        | Index register                    |                                                                           |                                                            | V ∨ Z (2), P0~P9 (10) |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
| Interrupt control                |                                           | External interrupt control        |                                                                           | 32 interrupts(16 points input positive/negative edge)      |                       |              |                                            |             |                                                                                                                                                                   | Only main unit input points                                                                     |                                                |
|                                  |                                           | Internal interrupt control        |                                                                           | 8 interrupts (1 ∨ 2 ∨ 3 ∨ 4 ∨ 5 ∨ 10 ∨ 50 ∨ 100mS)         |                       |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
| 0.1mS high-speed timer           |                                           |                                   |                                                                           | 1(16-bit), 4(32-bit, share with HHSC)                      |                       |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
| High-speed counter HSC           | Hardware high-speed counter (HHSC)/32-bit | No. of channel                    | Up to 4                                                                   |                                                            |                       |              |                                            |             | Total number of HHSC and SHSC is 8<br><br>HHSC can be converted into 32-bit/0.1mS time base High-Speed Timer(HST) Half of maximum frequency while A/B phase input |                                                                                                 |                                                |
|                                  |                                           | Counting mode                     | 8 modes (U/D ∨ U/Dx2 ∨ P/R ∨ P/Rx2 ∨ A/B ∨ A/Bx2 ∨ A/Bx3 ∨ A/Bx4)         |                                                            |                       |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
|                                  |                                           | Counting frequency                | Maximum is 50KHz (Singed-end input)                                       |                                                            |                       |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
|                                  | Software high-speed counter(SHSC)/32-bit  | No. of channel                    | Up to 4                                                                   |                                                            |                       |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
|                                  |                                           | Counting mode                     | 3 modes (U/D ∨ P/R ∨ A/B)                                                 |                                                            |                       |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
|                                  |                                           | Counting frequency                | Maximum sum up to 5KHz                                                    |                                                            |                       |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
| NC position pulse output (HSPSO) | Number of axis                            |                                   | Up to 4                                                                   |                                                            |                       |              |                                            |             | Half of the maximum while A/B phase output                                                                                                                        |                                                                                                 |                                                |
|                                  | Output frequency                          |                                   | Maximum is 50KHz (Singed-end input)                                       |                                                            |                       |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
|                                  | Pulse output mode                         |                                   | 3 modes (U/D ∨ P/R ∨ A/B)                                                 |                                                            |                       |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
|                                  | Programming method                        |                                   | Dedicated position language                                               |                                                            |                       |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
|                                  | Interpolation                             |                                   | Maximum 4 axes linear interpolation                                       |                                                            |                       |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
| HSPWM output                     | Number of points                          |                                   | Up to 4                                                                   |                                                            |                       |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
|                                  | Output frequency                          |                                   | 72Hz~18.432KHz (with 0.1%resolution)<br>720Hz~184.3KHz(with 1%resolution) |                                                            |                       |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
| Captured input                   | Points                                    |                                   | Maximum 36 points (All inputs in main unit come with this feature)        |                                                            |                       |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
|                                  | Minimum captured pulse width              |                                   | >10μS (for Ultra high/high speed input)                                   |                                                            |                       |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
|                                  |                                           |                                   | >47μS (for medium speed input)                                            |                                                            |                       |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
|                                  |                                           |                                   | >470μS (for medium/low speed input)                                       |                                                            |                       |              |                                            |             |                                                                                                                                                                   |                                                                                                 |                                                |
| Digital filter                   |                                           |                                   | X0 ~ X15                                                                  | Adjustable frequency 14KHz~1.8MHz                          |                       |              |                                            |             |                                                                                                                                                                   | Chosen by frequency at high frequency                                                           |                                                |
|                                  |                                           |                                   |                                                                           | Adjustable time constant 0.1~1.5mS/1~15mS(unit: 0.1mS/1mS) |                       |              |                                            |             |                                                                                                                                                                   | Chosen by time constant at low frequency                                                        |                                                |
|                                  |                                           |                                   |                                                                           |                                                            |                       | X16 ~ X35    | Time constant 1~15mS adjustable(unit: 1mS) |             |                                                                                                                                                                   |                                                                                                 |                                                |

Digital Input (DI) Specification


\* : Half of maximum frequency while A/B phase input

| Specification \ Item    |     | Main Unit                                                                          |                     |                        | Extension module | Note                                                                   |
|-------------------------|-----|------------------------------------------------------------------------------------|---------------------|------------------------|------------------|------------------------------------------------------------------------|
|                         |     | High speed(HHSC)                                                                   | Medium speed (SHSC) | Low speed (≥ X16)      | Low speed        |                                                                        |
| Maximum input frequency |     | 50KHz*                                                                             | Total 5KHz          | —                      | —                | HHSC: Hardware High speed counter<br>SHSC: Software High speed counter |
| Input signal voltage    |     | 24VDC±10%                                                                          |                     |                        |                  |                                                                        |
| Threshold current       | ON  | > 4mA                                                                              |                     | > 2.3mA                |                  |                                                                        |
|                         | OFF | < 1.5mA                                                                            |                     | < 0.9mA                |                  |                                                                        |
| Maximum input current   |     | 7.6mA                                                                              |                     | 4.5mA                  |                  |                                                                        |
| Input status indication |     | Displayed by LED: light when “ON”, dark when “OFF”                                 |                     |                        |                  |                                                                        |
| Isolation method        |     | Optical isolation, 500VAC, 1 minute                                                |                     |                        |                  |                                                                        |
| SINK/SOURCE selection   |     | Select by wiring methods (internal common terminal S/S and external common wiring) |                     |                        |                  |                                                                        |
| Noise filtering methods |     | AHF(0.42us)+DHF(14KHz~1.8MHz or 0.1~15ms)                                          |                     | AHF(0.2ms)+DHF(1~15ms) | AHF(1mS)         | DHF: Digital Hardware Filter<br>AHF: Analog Hardware Filter            |

Wiring of 24VDC single-end SINK input



Wiring of 24VDC single-end SOURCE input




Digital Output (DO) Specifications


\* : Half of maximum frequency while A/B phase output

| Specification                                        |           | Item              | High speed transistor output (Main unit HSPSO)     | Low speed transistor output | Single-end relay output                        | Note                                           |
|------------------------------------------------------|-----------|-------------------|----------------------------------------------------|-----------------------------|------------------------------------------------|------------------------------------------------|
| Maximum output frequency                             |           |                   | 50KHz*                                             | —                           | —                                              | HSPSO :<br>Hardware High Speed<br>Pulse Output |
| Working voltage                                      |           |                   | 5~30VDC                                            |                             | <250VAC/30VDC                                  |                                                |
| Maximum load current                                 | Resistive | 0.3A/0.1A (M4T/J) | 0.5A                                               | 2A/single, 4A/common        |                                                |                                                |
|                                                      | Inductive |                   |                                                    | 80VA(AC)/24VA(DC)           |                                                |                                                |
| Maximum voltage drop/conducting resistance (initial) |           | 0.5V              | 1V                                                 | 30mΩ (@1A, 6VDC)            |                                                |                                                |
| Minimum load                                         |           | —                 |                                                    | 2mA/DC power                |                                                |                                                |
| Leakage current                                      |           | < 0.1mA/30VDC     |                                                    | —                           |                                                |                                                |
| Maximum output delay time                            | ON → OFF  | 15μS              |                                                    | 10mS                        |                                                |                                                |
|                                                      | OFF → ON  | 30μS              |                                                    |                             |                                                |                                                |
| Output status indication                             |           |                   | Displayed by LED: light when "ON", dark when "OFF" |                             |                                                |                                                |
| Isolation method                                     |           |                   | Optical isolation, 500VAC, 1 minute                |                             | Electromagnetic isolation<br>1500VAC, 1 minute |                                                |


Wiring of relay single-end output




Wiring of transistor single-end SINK output




Wiring of transistor single-end SOURCE output



Wiring of M4T main unit Y0~Y7 transistor single-end SINK output



Wiring of M4J main unit Y0~Y7 transistor single-end SOURCE output



Model Specification



B1z Main Units

| Spec.              |                       | Model               | B1z-10MR                                    | B1z-10M(T/J)                                | B1z-14MR | B1z-14M(T/J)                                | B1z-20MR                                    | B1z-20M(T/J)                                | B1z-24MR                                    | B1z-24M(T/J)                                |
|--------------------|-----------------------|---------------------|---------------------------------------------|---------------------------------------------|----------|---------------------------------------------|---------------------------------------------|---------------------------------------------|---------------------------------------------|---------------------------------------------|
| Digital input      | 24VDC                 | High speed (50KHz)  | 4 points (2-axis single phase or A/B phase) |                                             |          |                                             | 6 points (3-axis single phase or A/B phase) |                                             | 8 points (4-axis single phase or A/B phase) |                                             |
|                    |                       | Medium (Total 5KHz) | 2 points                                    |                                             | 4 points |                                             | 6 points                                    |                                             | 6 points                                    |                                             |
|                    |                       | Low speed           | —                                           |                                             | —        |                                             | —                                           |                                             | —                                           |                                             |
| Digital Output     | Relay                 |                     | 4 points                                    | —                                           | 6 points | —                                           | 8 points                                    | —                                           | 10 points                                   | —                                           |
|                    | Transistor (5~30 VDC) | High speed (50KHz)  | —                                           | 2 points (1-axis single phase or A/B phase) | —        | 2 points (1-axis single phase or A/B phase) | —                                           | 4 points (2-axis single phase or A/B phase) | —                                           | 4 points (2-axis single phase or A/B phase) |
|                    |                       | Low speed           | —                                           | 2 points                                    | —        | 4 points                                    | —                                           | 4 points                                    | —                                           | 6 points                                    |
| Communication port |                       | Built-in            | 2 ports (Port0:RS232, Port2:RS485)          |                                             |          |                                             |                                             |                                             |                                             |                                             |
|                    |                       | Expandable          | —                                           |                                             |          |                                             |                                             |                                             |                                             |                                             |
| Calendar           |                       |                     | —                                           |                                             |          |                                             |                                             |                                             |                                             |                                             |
| Wiring mechanism   |                       |                     | 5mm European fixed terminal block           |                                             |          |                                             |                                             |                                             |                                             |                                             |
| Dimension          |                       |                     | Figure 1 (Standard), Figure 2 (Slim)        |                                             |          |                                             | Figure 3 (Standard), Figure 4 (Slim)        |                                             |                                             |                                             |





(Continue)

| Spec.            |            | Model     | B1-40XYR                             | B1-40XY(T/J) | B1-60XYR | B1-60XY(T/J)                         |
|------------------|------------|-----------|--------------------------------------|--------------|----------|--------------------------------------|
| Digital input    | 24VDC      | Low speed | 24                                   | 24           | 36       | 36                                   |
| Digital output   | Relay      | 2A        | 16                                   | —            | 24       | —                                    |
|                  | Transistor | 0.5A      | —                                    | 16           | —        | 24                                   |
| Wiring mechanism |            |           | 5mm European fixed terminal block    |              |          |                                      |
| Dimension        |            |           | Figure 5 (Standard), Figure 6 (slim) |              |          | Figure 7 (Standard), Figure 8 (slim) |

## Right side Analog I/O Expansion Modules

| Spec.                     | Model   | B1-6AD                                       | B1-2DA                                  |
|---------------------------|---------|----------------------------------------------|-----------------------------------------|
| Input point               |         | 6 points input                               | 2 points output                         |
| Input/Output value        |         | 12 bit                                       |                                         |
| Maximum resolution        |         | 1.22mV(Voltage), 2.44μA(Current)             |                                         |
| Input/Output signal range | Voltage | -10 ~ +10V, -5 ~ +5V, 0 ~ 10V, 0~5V          |                                         |
|                           | Current | -20 ~ +20mA, -10 ~ +10mA, 0 ~ 20mA, 0 ~ 10mA |                                         |
| Accuracy                  |         | ±1%                                          |                                         |
| Input impedance           |         | 63.2KΩ(Voltage)<br>250Ω(Current)             | —                                       |
| Conversion time           |         | Conversion once for each scan                |                                         |
| Maximum input signal      |         | ±12V(Voltage)<br>±24mA(Current)              | —                                       |
| Allowable load range      |         | —                                            | 500 ~ 1MΩ(Voltage)<br>0 ~ 500Ω(Current) |
| Isolation method          |         | Non-isolation                                |                                         |
| Wiring mechanism          |         | 3.81mm European fixed terminal block         |                                         |
| Dimension                 |         | Figure 9 (Standard), Figure 10 (slim)        |                                         |

## Right side Temperature Measurement Expansion Modules

| Spec.                                         | Model | B1-2TC/6TC                                                                                                                                      | B1-6RTD                                                                      |
|-----------------------------------------------|-------|-------------------------------------------------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------|
| Number of input points                        |       | 2 /6 points                                                                                                                                     | 6 points                                                                     |
| Sensor type and temperature measurement range |       | J ( -200~1200°C)<br>E (-190~1000°C)<br>K (-190~1300°C)<br>T (-190~380°C)<br>R ( 0~1800°C)<br>B (350~1800°C)<br>S ( 0~1700°C)<br>N (-200~1000°C) | 3-wire RTD sensor<br>(JIS or DIN)<br>Pt100(-200~850°C)<br>Pt1000(-200~600°C) |
| Temperature compensation                      |       | Built-in cold junction compensation                                                                                                             | —                                                                            |
| Resolution                                    |       | 0.1°C                                                                                                                                           |                                                                              |
| Temperature refresh time                      |       | Conversion once for each scan                                                                                                                   |                                                                              |
| Overall Precision                             |       | ± (1%+1°C)                                                                                                                                      | ± 1%                                                                         |
| Isolation method                              |       | Transform (power) and optical (signal) isolation, 500VAC, 1 minute, no isolation between each channel                                           |                                                                              |
| Power consumption                             |       | 24VDC -15%/+20%,2W max.                                                                                                                         |                                                                              |
| Wiring mechanism                              |       | 3.81 mm European fixed terminal block                                                                                                           |                                                                              |
| Dimension                                     |       | Figure 9 (Standard)                                                                                                                             |                                                                              |

**FBs Compatible Peripheral** (Refer to FBs-PLC Catalog for Detail Specifications)

| Memory Pack                                                                         | PWM/DA Module                                                                       | RFID card                                                                           | Simple HMI                                                                          | General Purpose Communication Converter                                             |                                                                                       |                                                                                       |
|-------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------|
| FBs-PACK                                                                            | PWM/DA                                                                              | CARD-H                                                                              | FBs-PEP/PEPR                                                                        | FBs-CM25C                                                                           | FBs-CM5R                                                                              | FBs-CM5H                                                                              |
|  |  |  |  |  |  |  |


| Bluetooth Communication Module                                                      | USB Converter Cable                                                                 | Port 0 Communication Cables                                                         |                                                                                     |                                                                                       |                                                                                       |
|-------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------|
| FBs-B2C                                                                             | FBs-U2C-MD-180                                                                      | FBs-232P0-9F-150                                                                    | FBs-232P0-9M-400                                                                    | FBs-232P0-MD-200                                                                      | FBs-232P0-MDR-200                                                                     |
|  |  |  |  |  |  |

## DC24V Power Supply


| 1A                                                                                  | 2A                                                                                  | 3A                                                                                  | 4A                                                                                  | 5A                                                                                    | 6A                                                                                    |
|-------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------|
| ADP-24V-1A                                                                          | ADP-24V-2A                                                                          | ADP-24V-3A                                                                          | ADP-24V-4A                                                                          | ADP-24V-5A                                                                            | ADP-24V-6A                                                                            |
|  |  |  |  |  |  |

## Dimensions


**Figure 1 10/14 points main units or expansion modules (standard)**




**Figure 2 10/14 points units or expansion modules (slim)**




**Figure 3 20/24 points main units or expansion modules (standard)**




**Figure 4 20/24 points main units or expansion modules (slim)**



**Figure 5 32/40 points main units or expansion modules (standard)**



**Figure 6 32/40 points main units of expansion modules (slim)**



**Figure 7 60 points  
main unit or expansion  
modules (standard)**




Figure 8 60 points main unit or expansion modules (Slim)




Figure 9 Right-side expansion (Standard)




Figure 10 Right-side expansion (Slim)




Figure 11 Left-side expansion (Standard)




Figure 12 Left-side expansion (Slim)




Figure 13 Left-side expansion (Standard)





Figure 14 Left-side expansion (Slim)



# Model List

| Item Name                   |                               | Module                                   | Specifications                                                                                                                                                                                                     |
|-----------------------------|-------------------------------|------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Main Units                  | B1z Main Units                | B1z-10M ◇ 25- ☆                          | 6 points 24VDC digital input (4 points 50 KHz, 2 points total 5KHz), 4 points relay output or transistor output (2 points 50KHz), RS232(Port 0)+RS485(Port 2) communication ports, both sides are not expandable   |
|                             |                               | B1z-14M ◇ 25- ☆                          | 8 points 24VDC digital input (4 points 50 KHz, 4 points total 5KHz), 6 points relay output or transistor output (2 points 50KHz), RS232(Port 0)+RS485(Port 2) communication ports, both sides are not expandable   |
|                             |                               | B1z-20M ◇ 25- ☆                          | 12 points 24VDC digital input (6 points 50 KHz, 6 points total 5KHz), 8 points relay output or transistor output (4 points 50KHz), RS232(Port 0)+RS485(Port 2) communication ports, both sides are not expandable  |
|                             |                               | B1z-24M ◇ 25- ☆                          | 14 points 24VDC digital input (8 points 50 KHz, 6 points total 5KHz), 10 points relay output or transistor output (4 points 50KHz), RS232(Port 0)+RS485(Port 2) communication ports, both sides are not expandable |
|                             |                               | B1z-32M ◇ 25- ☆                          | 20 points 24VDC digital input (8 points 50 KHz, 8 points total 5KHz), 12 points relay output or transistor output (6 points 50KHz), RS232(Port 0)+RS485(Port 2) communication ports, both sides are not expandable |
|                             |                               | B1z-40M ◇ 25- ☆                          | 24 points 24VDC digital input (8 points 50 KHz, 8 points total 5KHz), 16 points relay output or transistor output (6 points 50KHz), RS232(Port 0)+RS485(Port 2) communication ports, both sides are not expandable |
|                             |                               | B1z-60M ◇ 25- ☆                          | 36 points 24VDC digital input (8 points 50 KHz, 8 points total 5KHz), 24 points relay output or transistor output (8 points 50KHz), RS232(Port 0)+RS485(Port 2) communication ports, both sides are not expandable |
|                             | B1 Main Units                 | B1-10M ◇ 2- ☆                            | 6 points 24VDC digital input (4 points 50 KHz, 2 points total 5KHz), 4 points relay output or transistor output (2 points 50KHz), RS232(Port 0) communication port                                                 |
|                             |                               | B1-14M ◇ 2- ☆                            | 8 points 24VDC digital input (4 points 50 KHz, 4 points total 5KHz), 6 points relay output or transistor output (2 points 50KHz), RS232(Port 0) communication port                                                 |
|                             |                               | B1-20M ◇ 2- ☆                            | 12 points 24VDC digital input (6 points 50 KHz, 6 points total 5KHz), 8 points relay output or transistor output (4 points 50KHz), RS232(Port 0) communication port                                                |
|                             |                               | B1-24M ◇ 2- ☆                            | 14 points 24VDC digital input (8 points 50 KHz, 6 points total 5KHz), 10 points relay output or transistor output (4 points 50KHz), RS232(Port 0) communication port                                               |
|                             |                               | B1-32M ◇ 2- ☆                            | 20 points 24VDC digital input (8 points 50 KHz, 8 points total 5KHz), 12 points relay output or transistor output (6 points 50KHz), RS232(Port 0) communication port                                               |
|                             |                               | B1-40M ◇ 2- ☆                            | 24 points 24VDC digital input (8 points 50 KHz, 8 points total 5KHz), 16 points relay output or transistor output (6 points 50KHz), RS232(Port 0) communication port                                               |
|                             |                               | B1-60M ◇ 2- ☆                            | 36 points 24VDC digital input (8 points 50 KHz, 8 points total 5KHz), 24 points relay output or transistor output (8 points 50KHz), RS232(Port 0) communication port                                               |
|                             | 4-axis NC positioning Modules | B1-24M4(T/J)2-D24 ☆                      | 14 points 24VDC digital input (8 points 50 KHz, 6 points total 5KHz), 10 points transistor output (8 points 50KHz, 0.1A), RS232(Port 0) communication port, J is custom product                                    |
|                             |                               | B1-40M4(T/J)2-D24 ☆                      | 24 points 24VDC digital input (8 points 50 KHz, 8 points total 5KHz), 16 points transistor output (8 points 50KHz, 0.1A), RS232(Port 0) communication port, J is custom product                                    |
| Left Side Expansion Module  | Communication Modules         | B1-CM25E                                 | 1 port RS232 (Port 1) + 1 port RS485 (Port 2) + Ethernet network interface communication module                                                                                                                    |
|                             |                               | B1-CM55E                                 | 2 ports RS485 (Port 1, Port 2) + Ethernet network interface communication module                                                                                                                                   |
|                             |                               | B1-CM2 ☆                                 | 1 port RS232 (Port 2) communication module                                                                                                                                                                         |
|                             |                               | B1-CM22 ☆                                | 2 port RS232 (Port1, Port2) communication module                                                                                                                                                                   |
|                             |                               | B1-CM5 ☆                                 | 1 port RS485 (Port 2) communication module                                                                                                                                                                         |
|                             |                               | B1-CM55 ☆                                | 2 port RS485 (Port1, Port2) communication module                                                                                                                                                                   |
|                             |                               | B1-CM25 ☆                                | 1 port RS232 (Port 1) + 1 port RS485 (Port 2) communication module                                                                                                                                                 |
|                             | LAIO Modules                  | B1-L2DA ☆                                | Non-isolated 2 channels, 12-bit analog output module (0~10V or 0~20mA)                                                                                                                                             |
|                             |                               | B1-L4AD ☆                                | Non-isolated 4 channels, 12-bit analog input module (0~10V or 0~20mA)                                                                                                                                              |
|                             |                               | B1-L2A2D ☆                               | Non-isolated 2channels, 12-bit analog input + 2 channels, 12-bit analog output combo analog module (0~10V or 0~20mA)                                                                                               |
|                             | Temperature Modules           | B1-L4NTC ☆                               | 4 channels, NTC temperature input module, 12-bit resolution, measuring range 100Ω~100KΩ                                                                                                                            |
| Right Side Expansion Module | DIO Expansion Modules         | B1-4Y ◇ ☆                                | 4 points relay or transistor output                                                                                                                                                                                |
|                             |                               | B1-8X ☆                                  | 8 points 24VDC digital input                                                                                                                                                                                       |
|                             |                               | B1-8Y ◇ ☆                                | 8 points relay or transistor output                                                                                                                                                                                |
|                             |                               | B1-8XY ◇ ☆                               | 4 points 24VDC digital input, 4 points relay or transistor output                                                                                                                                                  |
|                             |                               | B1-16X ☆                                 | 16 points 24VDC digital input                                                                                                                                                                                      |
|                             |                               | B1-16Y ◇ ☆                               | 16 points relay or transistor output                                                                                                                                                                               |
|                             |                               | B1-16XY ◇ ☆                              | 8 points 24VDC digital input, 8 points relay or transistor output                                                                                                                                                  |
|                             |                               | B1-24XY ◇ ☆                              | 14 points 24VDC digital input, 10 points relay or transistor output                                                                                                                                                |
|                             |                               | B1-40XY ◇ ☆                              | 24 points 24VDC digital input, 16 points relay or transistor output                                                                                                                                                |
|                             |                               | B1-60XY ◇ ☆                              | 36 points 24VDC digital input, 24 points relay or transistor output                                                                                                                                                |
|                             | AIO Modules                   | B1-6AD ☆                                 | Non-isolated 6 channels, 12-bit analog input module (Voltage:-10~10V,-5~5V,0~5V Current: -20~20mA,-10~10mA,0~20mA,0~10mA)                                                                                          |
|                             |                               | B1-2DA ☆                                 | Non-isolated 2 channels, 12-bit analog output module (Voltage:-10~10V,-5~5V,0~5V Current: -20~20mA,-10~10mA,0~20mA,0~10mA)                                                                                         |
|                             | Temperature Modules           | B1-2/6TC                                 | 2/6 channels, thermocouple temperature input module with 0.1°C resolution, J, K, R, S, E, T, B, N thermocouple sensor                                                                                              |
|                             |                               | B1-6RTD                                  | 6 channels, RTD temperature input module with 0.1°C resolution, 3-wire RTD sensor (PT100 or PT1000)                                                                                                                |
|                             | FBs Compatible Peripheral     | Memory Pack                              | FBs-PACK PLC program memory pack with 20K Words program, 20K Words register                                                                                                                                        |
|                             |                               | PWMDA Module                             | PWMDA 10-bit single channel pules width modulation (PWM) 0~10V analog output (AO) module                                                                                                                           |
|                             |                               | RFID Card                                | CARD-H General purpose RFID (ISO-14443A Standard) (for FBs-PEPR)                                                                                                                                                   |
|                             |                               | Simple HMI                               | FBs-PEP/PEPR Multi-characters with graphics-based Parameter Entry Panel, built-in RFID Read/Write module with PEPR                                                                                                 |
|                             |                               | General Purpose Communication Converters | FBs-CM25C General purpose RS232 to RS485/RS422 communication interface converter with optical isolation                                                                                                            |
|                             |                               |                                          | FBs-CM5R General purpose RS485 repeater with optical isolation                                                                                                                                                     |
|                             |                               |                                          | FBs-CM5H General purpose 4 ports RS485 HUB with optical isolation, RS485 can be connected as star connection                                                                                                       |
|                             |                               | Bluetooth Communication Module           | FBs-B2C Bluetooth Module for PLC Main Unit Port 0                                                                                                                                                                  |
|                             |                               | USB Communication Converter              | FBs-U2C-MD-180 Communication converter cable with standard USB AM connector to RS232 Mini-DIN 4M connector (used in standard PC USB to FBs main unit Port0 RS232), length 180cm                                    |
|                             |                               | Port 0 Communication Cables              | FBs-232P0-9F-150 Mini-DIN 4M to DB9F communication cable (FBs main unit Port 0 RS232 connect to standard DB9M), length 150cm                                                                                       |
|                             |                               |                                          | FBs-232P0-9M-400 Mini-DIN 4M to DB9M communication cable (FBs main unit Port 0 RS232 connect to standard DB9F), length 400cm                                                                                       |
|                             |                               |                                          | FBs-232P0-MD-200 Mini-DIN 4M to Mini-DIN 4M communication cable (FBs main unit Port 0 RS232 connect to FBs-PEP/PEPR), length 200cm                                                                                 |
|                             |                               |                                          | FBs-232P0-MDR-200 Mini-DIN 4M to 90° Mini-DIN 4M communication cable (FBs main unit Port 0 RS232 connect to FBs-PEP/PEPR), length 200cm                                                                            |
| DC24V Power Supply          |                               | ADP-24V-1A                               | 90~240VAC Input Voltage, 50/60Hz, Output Voltage: 24VDC, Output Current: 1A, DIN-RAIL Type                                                                                                                         |
|                             |                               | ADP-24V-2A                               | 90~240VAC Input Voltage, 50/60Hz, Output Voltage: 24VDC, Output Current: 2A, DIN-RAIL Type                                                                                                                         |
|                             |                               | ADP-24V-3A                               | 90~240VAC Input Voltage, 50/60Hz, Output Voltage: 24VDC, Output Current: 3A, DIN-RAIL Type                                                                                                                         |
|                             |                               | ADP-24V-4A                               | 90~240VAC Input Voltage, 50/60Hz, Output Voltage: 24VDC, Output Current: 4A, DIN-RAIL Type                                                                                                                         |
|                             |                               | ADP-24V-5A                               | 90~240VAC Input Voltage, 50/60Hz, Output Voltage: 24VDC, Output Current: 5A, DIN-RAIL Type                                                                                                                         |
|                             |                               | ADP-24V-6A                               | 90~240VAC Input Voltage, 50/60Hz, Output Voltage: 24VDC, Output Current: 6A, DIN-RAIL Type                                                                                                                         |

◇ : R – Relay output, T. – Transistor SINK (NPN) output, J. – SOURCE (PNP) output

◎ : D24 – 21.6~28.8 VDC power supply, AC – 85~264 VAC power supply (customized products)

☆ : Blank – Standard case, -S – Slim case (units with AC power supply have no slim case)